



Motion Computing Software Release Note

Name	LE1700 BIOS A13
File Name	LE1700_BIOS_A13.zip
Release Date	March 10, 2008
This Version	A13
Replaces Version	A10 and all previous versions
Intended Users	Motion Computing advises all LE1700 users to install this update. See <i>Fixes in this Release</i> and <i>Known Issues and Limitations</i> below for more details.
Intended Product	LE1700 Tablet PCs with A versions of BIOS ONLY
File Size	610 KB
Supported Operating System	<ul style="list-style-type: none">• Windows XP Tablet PC Edition 2005* Version 2002 Service Pack 2• Windows Vista, all versions except Windows Vista Home Basic <p>* Tablet Edition 2005 is included with the free Service Pack 2 download. If you have installed Windows XP Service Pack 2 on a Tablet PC you have Tablet Edition 2005.</p>

Fixes in this Release

- Improved WWAN card detection.
- Approved WWAN cards are now automatically enabled by default.
- Added PXE Boot (network-based boot) function supporting additional LAN chips.

Known Issues and Limitations

- **Supports only LE1700 tablets shipping with A versions of BIOS**
Some LE1700 tablets ship with B versions of BIOS. **Do not attempt to install version A13 of BIOS on LE1700 tablets containing B versions of BIOS. See installation instructions below.**
- PXE boot (network-based boot) cannot be disabled in BIOS.
- Windows Vista ignores Critical Battery settings stored in BIOS. This is an issue with Windows Vista.

Installation and Configuration Instructions

To install the LE1700 A13 BIOS update:

1. **Verify** that the version of BIOS installed in the tablet is an **A** version by using System Information (Program Files > Accessories > System Tools). Look for the line labeled **BIOS Version/Date**. The BIOS version will start with a letter **A** or a letter **B**.

Processor	Intel(R) Core(TM)2 CPU	L7400 @ 1.50GHz, 1500 Mhz, ...
BIOS Version/Date	Motion Computing - LE1700	A.10.T03, 8/10/2007
SMBIOS Version	2.4	
Windows Directory	C:\Windows	

Note: If your BIOS starts with the letter **B**, a different BIOS file will be released to support your LE1700. **Do not attempt to install version A13 of BIOS on your tablet if the BIOS version starts with the letter B.**

2. Download the BIOS A13 file (LE1700_Bios_A13.zip) and save it to a directory of your choice.
3. Unzip the file to a location on your local drive.
4. Start WinPhlash. In Windows Vista, you can run WinPhlash as an Administrator by right-clicking the WinPhlash icon and selecting **Run as administrator**.
5. Select the LE1700_A13.wph BIOS file and click the **Flash BIOS** button.

Note: Shut down your tablet after installing the BIOS.

Licensing

Refer to your applicable end-user licensing agreement for usage terms.