

Release Notes - ET1N2 JB - BSP v02.20.2478 - Hotfix CFE v01.07.00 package

- [Introduction](#)
- [Description](#)
- [Package Details](#)
- [Device Compatibility](#)
- [Installation Requirements](#)
- [Installation Instructions](#)
- [Part Number and Release Date](#)

Introduction

HotFix CFE (Cumulative Fixes from Engineering) Package includes multiple SPR Hotfixes contained into a single package. The HotFix CFE Package helps the end users to keep up to date with all the SPR Hotfixes for given product software release / revision.

HotFix CFE packages are validated only by engineering validation team and the package follows Zebra Technologie's HotFix Package Policy. Click here to view HotFix Package Policy. [HotFix Support Policy](#)

Description

The Hot fixes that are included in this HotFix CFE_ET1N2_JB_02202478_EN_v010700_v1_0.zip are as follows:

SPR No	Synopsis
28484	Turning Off Airplane Mode will lead to User Notification pop-up which will not get closed.
27739	The Device occasionally scan the data on a new scan from a previous scan.
27826	WWAN data connection terminated in a few minutes after connection was established (ET1N2 ONLY).
27818	Roll-back the "Long-press Home key" function to Recent Application.
27779	Unhide the "Enable Mock Location" option from Settings.
28080	Fusion French localization issue.
28147	Android Security Patch for StageFright Vulnerability.

Contents

CFE_ET1N2_JB_02202478_EN_v010700_v1_0.zip

Device Compatibility

This software release has been approved for use with the following Zebra devices,

Device	Operating System	OEM Version
ET1N2	Android JB 4.1.1	v02.20.2478

Installation Requirements

This SW is intended for the ET1N0 device running ET1N2 02-4AJ11-2478-0200-00-D1-030215.

Installation Instructions

1. Copy updates zip to the root directory of SD card.
2. Place the SD card in the device to be upgraded and connect to A/C power.
3. Press and hold the Power button on the device until the Device options menu appears.
4. Tap on Reset to reboot the device.
5. When the device is rebooting hold the right Scan/Action button to enter Recovery update mode.
6. When the Recovery Mode screen appears release the Right Scan/Action button.
7. Tap Home key to access recovery menu screen.
8. Tap P1, P2 keys to navigate to "apply update from /sdcard" option.
9. Tap P3 to select this option.
10. Tap P1, P2 keys to navigate to the update zip file.
11. Tap P3 to select this option.
12. After pressing P3, the upgrade will start.
13. After upgrading successfully, the screen will back to Recovery mode menu.
14. Tap P1, P2 keys to navigate to the "reboot system now" option.
15. Tap P3 to select this option.
16. After pressing P3 system will reboot.

Part Number and Release Date

January 2016